



Spektrum Air Receivers

Item	Description	Channel Outputs	Channel Inputs	Smart Compatible	Programmable AS3X	Programmable Safe	User Updateable	Bind Method	Modulation	Remote RX Ports	XBUS Port	Serial Data Protocol	Integrated Variometer	Integrated Telemetry	Telemetry Range	Failsafe Type	Dimensions	Weight	Antenna Length	Input Voltage	Suggested Application							
																					Micro/ Indoor	Park Flyer	Club/Large Field	Giant Scale	Carbon Fuse	Flybar Heli	Flybarless Heli	MultiRotor
SPMFC6250HX	FC6250HX Helicopter Flybarless Control System	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	2	Yes	SRXL2	No	Yes	Full Range	Smart Safe + Hold Last	0.94" (24mm)x 0.53" (13.6mm)	0.46oz (13g)	N/A	3.5V- 8.5V							X	
SPMAR8020T	AR8020T 8-Channel Integrated Telemetry Receiver	8	8	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	1	Yes	SRXL2	Yes	Yes	Full Range	Preset , Smart Safe + Hold Last	1.92" (49 mm) x 1.18" (30 mm)	0.56 oz (16 g)	6.1" (155 mm)	3.5V - 9V		X	X	X	X	X		
SPM-1033	AR8360T+ 8-Channel AS3X+ / SAFE Telemetry Rx	8	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	1	Yes	SRXL2	Yes	Yes	Full Range	Preset , Smart Safe + Hold Last	1.92" (49 mm) x 1.18" (30 mm)	0.56 oz (16 g)	6.1" (155 mm)	3.5V - 9V		X	X	X	X			
SPMAR620	AR620 6-Channel Sport Receiver	6	6	Yes	No	No	Yes	Button	DSMX/DSM2	0	No	None	No	Yes	Fly By	Smart Safe + Hold Last	1.04 in (26.4mm)x0.71 in (17.9mm)	0.28 oz (8g)	NA (Internal PCB)	3.5V - 9V		X	X					
SPMAR6610T	AR6610T 6-Channel Integrated Telemetry RX	6	6	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	1	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	0.94" (23.3mm)x 0.595" (15.02mm)	0.42oz (12g)	6.10" (155mm) and 7.32" (186mm)	3.5V - 9V		X	X		X	X		
SPMAR410	AR410 4-Channel Sport Receiver	4	4	Yes	No	No	Yes	Button	DSMX/DSM2	0	No	None	No	Yes	Fly By	Smart Safe + Hold Last	0.79 in (20.0mm)x0.55 in (13.9mm)	0.25 oz (7 g)	NA (Internal PCB)	3.5V - 9v	X	X	X					
SPM-1032	AR637T+ 6-Channel AS3X+ / SAFE Telemetry Rx	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	1	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	0.94" (23.3mm)x 0.595" (15.02mm)	0.42oz (12g)	6.10" (155mm) and 7.32" (186mm)	3.5V - 9V		X	X		X			
SPM-1030	AR630+ 6-Channel AS3X+ / SAFE Receiver	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	0	No	SRXL2	No	Yes	Fly By	Preset , Smart Safe + Hold Last	1.85" (47 mm) x 0.98" (25 mm)	0.021lbs (10g)	NA (Internal PCB)	3.5V - 9V		X	X					
SPM-1031	AR631+ 6-Channel AS3X+ / SAFE Receiver	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	0	No	SRXL2	No	Yes	Fly By	Preset , Smart Safe + Hold Last	1.53 in (39mm)x 0.95 in (24mm)	0.328oz (9.3g)	9 in (230mm)	3.5 - 9V		X	X		X			
SPM4650	DSMX SRXL2 Serial Micro Receiver	20	20	Yes	No	No	Yes	Button	DSMX/DSM2	0	No	SRXL2	No	Yes	Fly By	Smart Safe + Hold Last	0.51" (13mm)x 0.20" (5mm)	0.05oz (1.4g)	3.9" (100mm)	3.3V- 8.4V	X		X			X	X	
SPM4651T	DSMX SRXL2 Serial Receiver with Telemetry	20	20	Yes	No	No	Yes	Button	DSMX/DSM2	0	No	SRXL2	No	Yes	Full Range	Smart Safe + Hold Last	0.71" (18mm)x 0.31" (7.8mm)	0.14oz (4g)	3.9" (100mm)	3.3V - 8.4V					X	X		
SPMAR10100T	AR10100T DSMX 10-Channel Telemetry RX	10	10	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	2	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.16 x 1.18 x 0.59 in (55 x 30 x 15mm)	18g	7.32" (186 mm)	3.5V~9V			X	X	X			
SPM-1034	AR10360T+ 10-Channel AS3X+ / SAFE Telemetry Rx	10	10	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	2	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.16 x 1.18 x 0.59 in (55 x 30 x 15mm)	18g	7.32" (186 mm)	3.5V~9V			X	X	X			
SPMAR10410T	AR10410T 10-Channel PowerSafe Telemetry Receiver	10	10	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	4	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.6" (66mm) x 2.44" (62mm) x .67" (17mm)	1.9 oz (54g)	N/A	3.5-12.6V			X	X	X			
SPMAR14410T	AR14410T 14-Channel PowerSafe Telemetry Receiver	14	14	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	4	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.6" (6mm) x 2.2" (56mm)	2.8 oz (80g)	N/A	3.5-12.6V			X	X	X			
SPMAR20410T	AR20410T 20-Channel PowerSafe Telemetry Receiver	20	20	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	4	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.56" (65mm) x .71" (18mm)	3.0 oz (86g)	N/A	3.5-12.6V			X	X	X			
SPM9745	DSMX Remote Receiver	20	20	No	No	No	No	Plug	DSMX/DSM2	0	0	None	No	No	N/A	Smart Safe + Hold Last	0.8"(20.6mm) x 1.02"(26mm) x 0.27"(6.75mm)	0.12oz(3.35g)	2.44"(62mm)	3.3V								
SPM9746	DSMX Carbon Fiber Remote Receiver	20	20	No	No	No	No	Plug	DSMX/DSM2	0	0	None	No	No	N/A	Smart Safe + Hold Last	0.8"(20.6mm) x 1.02"(26mm) x 0.27"(6.75mm)	0.12oz(3.35g)	9.09"(231mm)	3.3V								
SPM9747	SRXL2 DSMX Remote Receiver	20	20	Yes	No	No	Yes	Button	DSMX/DSM2	0	No	SRXL2	No	Yes	Full Range	Smart Safe + Hold Last	1" (25.4mm) x 0.71" (18.11mm)	0.1oz (3g)	NA (Internal PCB)	3.3v - 8.4V		X	X	X		X	X	
Discontinued																												
SPMAS6410NBL	AS6410NBL DSMX 6Ch AS3X Receiver with BL ESC	6	6	No	Yes	No	Yes	Autobind	DSMX/DSM2	0	No	None	No	No	NA	Smart Safe + Hold Last			1.2" (31mm)	3.3V - 8.4V	X	X						
SPMAR10400T	AR10400T 10-Channel PowerSafe Telemetry Receiver	10	10	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	4	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.6" (66mm) x 2.44" (62mm) x .67" (17mm)	1.9 oz (54g)	N/A	3.5-12.6V			X	X	X			
SPMAR14400T	AR14400T 14-Channel PowerSafe Telemetry Receiver	14	14	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	4	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.6" (6mm) x 2.2" (56mm)	2.8 oz (80g)	N/A	3.5-12.6V			X	X	X			
SPMAR20400T	AR20400T 20-Channel PowerSafe Telemetry Receiver	20	20	Yes	No	No	Yes	Button & Plug	DSMX/DSM2	4	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.56" (65mm) x .71" (18mm)	3.0 oz (86g)	N/A	3.5-12.6V			X	X	X			
SPMAR8360T	AR8360T 8-Channel AS3X & SAFE Receiver	8	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	1	Yes	SRXL2	Yes	Yes	Full Range	Preset , Smart Safe + Hold Last	1.92" (49 mm) x 1.18" (30 mm)	0.56 oz (16 g)	6.1" (155 mm)	3.5V - 9V		X	X	X	X			
SPMAR637T	AR637T 6-Channel AS3X & SAFE Telemetry Rx	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	1	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	0.94" (23.3mm)x 0.595" (15.02mm)	0.42oz (12g)	6.10" (155mm) and 7.32" (186mm)	3.5V - 9V		X	X		X			
SPMAR630	AR630 6-Channel AS3X & SAFE Receiver	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	0	No	SRXL2	No	Yes	Fly By	Preset , Smart Safe + Hold Last	1.85" (47 mm) x 0.98" (25 mm)	0.021lbs (10g)	NA (Internal PCB)	3.5V - 9V		X	X					
SPMAR631	AR631 6-Channel AS3X & SAFE Receiver	6	20	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	0	No	SRXL2	No	Yes	Fly By	Preset , Smart Safe + Hold Last	1.53 in (39mm)x 0.95 in (24mm)	0.328oz (9.3g)	9 in (230mm)	3.5 - 9V		X	X		X			
SPMAR10360T	AR10360T DSMX 10-Channel AS3X & SAFE Telemetry RX	10	10	Yes	Yes	Yes	Yes	Button & Plug	DSMX/DSM2	2	Yes	SRXL2	Yes	Yes	Full Range	Preset, Smart Safe + Hold Last	2.16 x 1.18 x 0.59 in (55 x 30 x 15mm)	18g	7.32" (186 mm)	3.5V~9V			X	X	X			
SPMAR12310T	AR12310T 12CH PowerSafe Integrated Telemetry RX	12	20	No	Yes (with AS3000)	No	Yes	Button & Plug	DSMX/DSM2	3	Yes	X-Plus	No	Yes	Full Range	Preset, Smart Safe + Hold Last	2.2 in (55.94mm)x 0.7 in (17.73mm)	48.19g		3.5V- 10V				X				
SPMAR9320T	AR9320T 9CH Carbon Fuse Integrated Telemetry RX	9	9	No	No	No	Yes	Button & Plug	DSMX/DSM2	2	Yes	X-Plus	Yes	Yes	Full Range	Preset , Smart Safe + Hold Last	1.11 in (28.3 mm)x 0.82 in (20.9 mm)	0.63 oz (17.83 g)		3.5V - 9V		X	X	X	X			
SPMAR8010T	AR8010T 8CH Air Integrated Telemetry Receiver	8	8	No	No	No	Yes	Button & Plug	DSMX/DSM2	3	Yes	X-Plus	No	Yes	Full Range	Smart Safe + Hold Last				3.5V - 9V			X	X		X		
SPMAR12120	AR12120 12CH Powersafe Receiver	12	12	No	No	No	No	Plug	DSMX/DSM2	4	No	X-Plus	No	No	NA	Smart Safe + Hold Last			31mm	6V - 10V				X				
SPMAR9140T	AR9140T 9CH Powersafe Integrated Telemetry Receiver	9	9	No	Yes (with AS3000)	No	Yes	Button &																				